



M230E...

- 1- For proper utilization of this product and safety, it is mandatory to closely comply with the directions and notes in this instruction and guide.
- 2- Do not directly touch or impact LED module.
- 3- Do not stare at LED light source.



Lighting Control Switch

Detection Range				Hold Time				Daylight Sensor				
<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	100%	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	5s	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	2Lux	ON OFF
<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	75%	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	30s	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	10Lux	
<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	50%	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	1min	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	25Lux	
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	25%	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	3min	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	50Lux	
				<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	5min	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	Disable	
				<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	10min					
				<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	20min					
				<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	30min					

M230EMS...

Lighting Control Switch

Detection Range

- If numbers 1&2 are ON, the sensor sensitivity performance sets on 100%.
- If number 1 is ON and number 2 is OFF the sensor sensitivity performance sets on 75%.
- If number 1 is OFF and number 2 is ON the sensor sensitivity performance sets on 50%.
- If numbers 1&2 are OFF, the sensor sensitivity performance sets on 25%.

Hold Time

- If numbers 3&4&5 are ON, the sensor stays on for 5 seconds after motion detection
- If numbers 3&4 is ON and numbers 5 is OFF, the sensor stays on for 30 seconds after motion detection
- If number 3&5 is ON and number 4 is OFF, the sensor stays on for 1 minutes after motion detection
- If numbers 4&5 are OFF and number 3 is ON, the sensor stays on for 3 minutes after motion detection
- If numbers 4&5 is ON and numbers 3 is OFF, the sensor stays on for 5 minutes after motion detection
- If numbers 3&5 are OFF and number 4 is ON, the sensor stays on for 10 minutes after motion detection
- If numbers 3&4 are OFF and number 5 is ON, the sensor stays on for 20 minutes after motion detection
- If numbers 3&4&5 are OFF, the sensor stays on for 30 minutes after motion detection

Daylight Sensor

- Numbers 6&7&8 must be always OFF.

Note: The optimal settings for the lighting control switch will be as shown in the table below:

