



Cat. No.	Projected Area (m ²)	Maximum number of luminaires per MCB (MCB Type B, C)						W (kg)
		B16	B25	B32	C16	C25	C32	
M311S...LED3...-S	0.08	50	78	101	85	130	171	3.8
M311S...LED4...-S	0.08	50	78	101	85	130	171	4.5
M311S...LED6...-S	0.08	50	78	101	85	130	171	4.5
M311...LED7...-S	0.156	11	17	23	18	28	37	7.0
M311...LED9...-S	0.156	2	3	4	3	5	7	7.4



- 1- For proper utilization of this product and safety, it is mandatory to closely comply with the directions and notes in this instruction and guide.
- 2- Earth connection as provided is mandatory.
- 3- Do not directly touch or impact LED module.
- 4- Do not stare at LED light source.
- 5- The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person. Always switch off the power prior to installation, maintenance or repair activities.

In order to use the brackets, follow their individual manual instructions for mounting.

